



Tech Info Library

Super Serial Card: DIP Switch Settings

Revised: 11/7/88
Security: Everyone

Super Serial Card: DIP Switch Settings

=====

This article last reviewed: 1 November 1988

"PRINTER MODE"

MODE SELECTION

Printer Mode -> SW1-5:Off, SW1-6:On
SIC P8 Emulation Mode -> SW1-5:On, SW1-6:Off
SIC P8A Emulation Mode -> SW1-5:Off, SW1-6:Off

SPECIAL SWITCHES

Interrupts OFF -> SW2-6:Off
Interrupts On -> SW2-6:On
Normal Clear to Send -> SW1-7:On, SW2-7:Off
Second Clear to Send -> SW1-7:Off, SW2-7:On

BPS (BAUD) RATE

undefined -> SW1-1:On, SW1-2:On, SW1-3:On, SW1-4:On
50 -> SW1-1:On, SW1-2:On, SW1-3:On, SW1-4:Off
75 -> SW1-1:On, SW1-2:On, SW1-3:Off, SW1-4:On
109.92 (110) -> SW1-1:On, SW1-2:On, SW1-3:Off, SW1-4:Off
134.58 (135) -> SW1-1:Off, SW1-2:Off, SW1-3:On, SW1-4:On
150 -> SW1-1:On, SW1-2:Off, SW1-3:On, SW1-4:Off
300 -> SW1-1:On, SW1-2:Off, SW1-3:Off, SW1-4:On
600 -> SW1-1:On, SW1-2:Off, SW1-3:Off, SW1-4:Off
1200 -> SW1-1:Off, SW1-2:On, SW1-3:On, SW1-4:On
1800 -> SW1-1:Off, SW1-2:On, SW1-3:On, SW1-4:Off
2400 -> SW1-1:Off, SW1-2:On, SW1-3:Off, SW1-4:On
3600 -> SW1-1:Off, SW1-2:On, SW1-3:Off, SW1-4:Off
4800 -> SW1-1:Off, SW1-2:Off, SW1-3:On, SW1-4:On
7200 -> SW1-1:Off, SW1-2:Off, SW1-3:On, SW1-4:Off
9600 -> SW1-1:Off, SW1-2:Off, SW1-3:Off, SW1-4:On
19200 -> SW1-1:Off, SW1-2:Off, SW1-3:Off, SW1-4:Off

DATA FORMAT

8 data, 1 stop -> SW2-1:On

8 data, 2 stop -> SW2-1:Off

LINE WIDTH/VIDEO

40/video on -> SW2-3:On, SW2-4:On
72/video off -> SW2-3:On, SW2-4:Off
80/video off -> SW2-3:Off, SW2-4:On
132/video off -> SW2-3:Off, SW2-4:Off

DELAY AFTER <CR> OUT

none -> SW2-2:Off
32ns -> SW2-2:On

GEN <LF> AFTER <CR>

yes -> SW2-5:On
no -> SW2-5:Off

"COMMUNICATIONS MODE"

MODE SELECTION

Communications Mode -> SW1-5:On, SW1-6:On

SPECIAL SWITCHES

Interrupts OFF -> SW2-6:Off
Interrupts On -> SW2-6:On
RS-232-C Signals -> SW1-7:On, SW2-7:Off

BPS RATE (same as above in "PRINTER MODE")

DATA FORMAT

8 data, 1 stop -> SW2-1:On, SW2-2:On
7 data, 1 stop -> SW2-1:On, SW2-2:Off
8 data, 2 stop -> SW2-1:Off, SW2-2:On
7 data, 2 stop -> SW2-1:Off, SW2-2:Off

PARITY (for info search on ASCII and PARITY)

none -> SW2-4:On
odd -> SW2-3:On, SW2-4:Off
even -> SW2-3:Off, SW2-4:Off

GEN <LF> AFTER <CR> (same as above in "PRINTER MODE")

Copyright 1988 Apple Computer, Inc.

Tech Info Library Article Number:1387