



Tech Info Library

A/UX: Setup for Modem Autoanswer (8/94)

Revised: 8/25/94
Security: Everyone

A/UX: Setup for Modem Autoanswer (8/94)

=====
Article Created: 29 October 1990
Article Reviewed/Updated: 25 August 1994

TOPIC -----

What setting is necessary to have a 1200 baud modem autoanswer from the modem port?

DISCUSSION -----

In A/UX, if you have a problem talking with the modem, first try running `stty -g /dev/tty0 -modem`. This will disable modem control on the modem port. In the `/etc/inittab` subdirectory, make two changes to the line for the modem port as follows:

- change the "off" to "respawn"
- change the "at_9600" to "mo_1200"

Note: If you have a 2400 baud modem, the last expression should be "mo_2400".

Article Change History:
25 Aug 1994 - Reviewed and updated.

Support Information Services

Copyright 1990, 1994 Apple Computer, Inc.

Tech Info Library Article Number:6476