

Tech Info Library

TITLE

Apple Remote Access: Error Codes

Article ID: 16456
Created: 10/6/94
Modified: 10/12/98

TOPIC

This article lists Apple Remote Access' (ARA) error codes.

DISCUSSION

USERS & GROUPS DATABASE

-
- 1 ugUserAlreadyExists
 - 2 ugGroupAlreadyExists
 - 3 ugULInfoRecNotCreated
 - 4 ugNoMoreUGs
 - 5 ugUserNotFound
 - 6 ugGroupNotFound
 - 7 ugNotAUser
 - 8 ugNotAGroup
 - 9 ugTooManyGroups
 - 10 ugNotaMember
 - 11 ugNoMoreUsers
 - 12 ugNoMoreGroups
 - 13 ugBadParamErr
 - 14 ugUserAlreadyAMember
 - 15 ugAPrmaryGroupExists
 - 16 ugServerRunning
 - 17 ugAdminRunning
 - 18 ugNotBtree
 - 19 ugBadKey
 - 20 ugDskFull
 - 21 ugBadUID
 - 22 ugInvalidPasswd
 - 23 ugEOF
 - 24 ugBOF
 - 25 ugUserConnected
 - 26 ugNoMoreEirs
 - 27 ugEirNotFound
 - 28 ugEirInternalErr
-
- 97 ugFSRunning
 - 98 ugDefNameErr
 - 99 ugFatalError

NETSHARE MANAGER

-
- 5808 ERR_ZONEBUFBADSIZE
 - 5809 ERR_CONNECTTIMEDOUT
 - 5810 ERR_CONNECTUSERTIMEDOUT
 - 5811 ERR_BADPARAMETER

- 5812 ERR_NOMULTINODE
- 5813 ERR_ATALKNOTACTIVE
- 5814 ERR_NOCALLBACKSUPPORT
- 5815 ERR_NOTOPENEDBYTHISPB
- 5816 ERR_NOGLOBALS
- 5817 ERR_NOSMARTBUFFER
- 5818 ERR_BADATAALKVERS
- 5819 ERR_VLD8_CALLBACK
- 5820 ERR_VLD8_BADVERSION
- 5821 ERR_VLD8_BADUSER
- 5822 ERR_VLD8_BADPASSWORD
- 5823 ERR_VLD8_BADLINK
- 5824 ERR_VLD8_NOCALLBACKALLOWED
- 5825 ERR_VLD8_ALLCBSERVERSBUSY - All of the Callback Clients are in use
- 5826 ERR_VLD8_GUESTNOTALLOWED
- 5827 ERR_VLD8_SERVERISIMPOSTER
- 5828 ERR_VLD8_LOGINNOTENABLED
- 5829 ERR_REMOTEPORTALREADYEXISTS
- 5830 ERR_OPENNOTALLOWED
- 5831 ERR_NOUSERSANDGROUPS
- 5832 ERR_PORTSHUTDOWN
- 5833 ERR_PORTDOESNOTEXIST
- 5834 ERR_PWNEEDEDFOREENABLE
- 5835 ERR_DAMAGED - The ARA file has been modified
- 5836 ERR_NETCONFIGCHANGED

----- tasn-all errors below this point are new as of 2.0 -----

- 5837 ERR_NOSUPPORT_ATREMOTE
- 5838 ERR_CANTCHANGE PW
- 5839 ERR_VLD8_INVALIDAUTHMETHOD
- 5840 ERR_VLD8_CONTINUE
- 5841 ERR_PWCHANGECANCEL
- 5842 ERR_EXTAUTH_MODULE_NOTFOUND - Client does not have a needed security module
- 5843 ERR_EXTAUTH_MODULE_BADVERSION - Incorrect version of a security module
- 5844 ERR_EXTAUTH_MODULE_BADRESULT - Client has returned some error in the result field
- 5845 ERR_EXTAUTH_MODULE_REJECT_USER - Module is rejecting this user

LINKTOOL MANAGER

-
- 5901 ERR_LTM_LISTENER_ID_IN_USE - Specified Listener identifier is in use
 - 5902 ERR_LTM_NO_LISTENER - Listener of specified type is not available
 - 5903 ERR_LTM_RESOURCE_NOT_REGISTERED - Listener of specified type is not available
 - 5904 ERR_LTM_PORT_NOT_CLAIMED - claim request failed because port is busy
 - 5905 ERR_LTM_COMMAND_NOT_ALLOWED - LTM command not allowed on specified port
 - 5906 ERR_LTM_BAD_VERSION - connect failed due to incompatible LTM versions
 - 5907 ERR_LTM_ARBITRATION_TIMEOUT - Time out during the listener arbitration.
 - 5908 ERR_LTM_KODE_NOT_FOUND - kode resource not found in specified file fail.
 - 5910 ERR_LTM_RESOURCE_CLAIMED - call failed because resource is already claimed
 - 5911 ERR_LTM_PORT_RESOURCES_CLAIMED - Port's resources are already claimed
 - 5912 ERR_LTM_RESOURCE_NOT_CLAIMED - call failed because the resource was unclaimed
 - 5913 ERR_LTM_PORT_RESOURCES_NOT_CLAIMED - The LTM port's resources are NOT claimed.
 - 5914 ERR_LTM_PORT_UNCLAIMED - LTM listen port unclaimed
 - 5915 ERR_LTM_CONNECTION_REFUSED - LTM listener refused connect request
 - 5916 ERR_LTM_CLAIM_ABORTED - LTM claim call aborted due to LTM_ARB_CLAIM_CANCEL call
 - 5917 ERR_LTM_END_OF_PORT_LIST - End of open port list reached in current port status session
 - 5918 ERR_LTM_NOT_CONNECTED - Not connected.
 - 5919 ERR_LTM_CONNECTION_ABORTED - Connection request aborted
 - 5920 ERR_LTM_BAD_LENGTH - Length of write request exceeds maximum.
 - 5921 ERR_LTM_BAD_PARAMETER - Bad parameter.
 - 5922 ERR_LTM_COMMAND_IN_PROGRESS - Command already in progress.
 - 5923 ERR_LTM_CONNECTED - Connection established.
 - 5924 ERR_LTM_CONNECT_CANCELED - Connection request canceled.
 - 5925 ERR_LTM_CONNECT_TIMEDOUT - Connection time out.

..TIL16456-Apple_Remote_Access_Error_Codes_(TA32644).pdf

- 5926 ERR_LTM_NO_DEFAULTS - Could not get default info...
- 5927 ERR_LTM_GOOD_BYE - The driver is going away in a rude fashion
- 5928 ERR_LTM_BAD_CHECKSUM - Bad checksum in framer
- 5929 ERR_LTM_BAD_PROTOCOL - Bad protocol type in PPP frame
- 5930 ERR_LTM_BAD_FRAME - Bad PPP frame

AR2

- 6051 ERR_MNP_NEGOTIATION_FAILURE - Connection parameter negotiation failure
- 6052 ERR_MNP_CONNECT_TIME_OUT - Connect request (acceptor mode) timed out
- 6053 ERR_MNP_NOT_CONNECTED - Not connected
- 6054 ERR_MNP_ABORTED - Request aborted by disconnect request
- 6055 ERR_MNP_ATTENTION_DISABLED - Link attention service is not enabled
- 6056 ERR_MNP_CONNECT_RETRY_LIMIT - Connect (initiator mode) request retry limit reached.
- 6057 ERR_MNP_COMMAND_IN_PROGRESS - Command already in progress.
- 6058 ERR_MNP_ALREADY_CONNECTED - Connection already established.
- 6059 ERR_MNP_INCOMPATIBLE_PROT_LVL - Connection failed due to incompatible protocol levels
- 6060 ERR_MNP_HANDSHAKE_FAILURE - Connection handshake failed.

MODEM CCL

- 6000 cclErr_AbortMatchRead - internal error used to abort match read
- 6006 cclErr - CCL error base
- 6007 cclErr_CloseError - There is at least one script open
- 6008 cclErr_ScriptCancelled - Script Canceled
- 6009 cclErr_TooManyLines - Script contains too many lines
- 6010 cclErr_ScriptTooBig - Script contains too many characters
- 6011 cclErr_NotInitialized - CCL has not been initialized
- 6012 cclErr_CancelInProgress - Cancel in progress.
- 6013 cclErr_PlayInProgress - Play command already in progress.
- 6014 cclErr_ExitOK - Exit with no error.
- 6015 cclErr_BadLabel - Label out of range.
- 6016 cclErr_BadCommand - Bad command.
- 6017 cclErr_EndOfScriptErr - End of script reached, expecting Exit.
- 6018 cclErr_MatchStrIdxErr - Match string index is out of bounds.
- 6019 cclErr_ModemErr - Modem error, modem not responding.
- 6020 cclErr_NoDialTone - No dial tone.
- 6021 cclErr_NoCarrierErr - No carrier.
- 6022 cclErr_LineBusyErr - Line busy.
- 6023 cclErr_NoAnswerErr - No answer.
- 6024 cclErr_NoOriginateLabel - No @ORIGINATE label
- 6025 cclErr_NoAnswerLabel - No @ANSWER label
- 6026 cclErr_NoHangUpLabel - No @HANGUP label

ARA 3.0 Scripting

- 7102 - Remote Access did not load properly at system startup
- 7103 - Remote Access could not set up a port
- 7104 - Remote Access is out of memory
- 7105 - The requested action is not supported
- 7106 - One or more resources are missing from Remote Access installed files
- 7107 - The Remote Access Connections file is not compatible with the installed version of Remote Access
- 7108 - An action requiring a connection was requested when there was no connection
- 7109 - The connection attempt or established connection was terminated by the user
- 7112 - An unexpected error with no useful information has occurred
- 7113 - One or more of the installed Remote Access files is damaged
- 7114 - The requested action could not be performed because Remote Access was busy
- 7115 - The Remote Access logical port is in an unknown state
- 7116 - The Remote Access logical port is in an invalid state
- 7117 - The Remote Access logical port has detected an invalid serial protocol
- 7118 - Login is disabled for the given user
- 7120 - The server administrator requires the user to enter a password

..TIL16456-Apple_Remote_Access_Error_Codes_(TA32644).pdf

- 7122 - Remote Access could not initialize Open Transport
- 7123 - The requested action could not be performed because Remote Access is not fully initialized yet
- 7124 - TCP/IP is inactive and can not be loaded
- 7125 - TCP/IP is not yet configured
- 7126 - PPP is not selected as the TCP/IP interface in the current TCP/IP configuration
- 7128 - The requested PPP protocol was rejected by the PPP peer
- 7129 - User authentication failed
- 7130 - PPP negotiation failed
- 7131 - Connection was lost unexpectedly
- 7132 - The remote side disconnected unexpectedly
- 7133 - The remote side is not responding
- 7151 - The Remote Access log file is not open
- 7152 - The Remote Access log file is already open
- 7153 - The Remote Access log entry could not be retrieved
- 7155 - Remote Access cannot locate the active System Folder
- 7156 - Remote Access cannot locate its Preferences folder
- 7157 - There is a preexisting file using a Remote Access type or creator
- 7158 - There is a preexisting folder using a Remote Access folder name and location
- 7159 - The Remote Access Connections file is not open
- 7161 - An unknown control protocol type was received
- 7162 - Remote Access received a packet with an invalid length
- 7163 - Remote Access received a negotiable option with an invalid value
- 7164 - Remote Access received a negotiable option with invalid flags
- 7165 - Remote Access ran out of memory while negotiating with the peer
- 7169 - Remote Access encountered an error with no useful information
- 7170 - Remote Access is in an invalid state
- 7180 - The user canceled the password entry dialog
- 7181 - The user did not respond to the password entry dialog in time
- 7182 - An unknown serial port was referenced
- 7183 - The Remote Access logical port is not configured
- 7184 - No AppleTalk services endpoints are available
- 7185 - The modem script ASK or manual dialing dialog was canceled by the user

EXTENDED Information - [Apple Internal Use - Service Providers and Support Professional](#)

Document Information

Product Area: Apple Software; Communications-Networking

Category: Apple Remote Access (ARA)

Sub Category: General Topics

APPLE NEED-TO-KNOW CONFIDENTIAL: Do NOT forward, copy, or otherwise replicate or disseminate verbally, electronically, or in hardcopy (except to those individuals within your organization who have a legitimate business need to know the information, and who have agreed in writing, to keep it confidential), unless Apple has given prior written authorization.

Copyright © 1999-2000, Apple Computer, Inc.