



Tech Info Library

Silentype and the TAB command

Revised: 7/30/87
Security: Everyone

Silentype and the TAB command

=====

TABS do not work properly with the Silentype. From Integer BASIC, the tab is limited to the first 40 columns, while an Applesoft TAB(20) occassionally outputs 20 spaces instead of going to column 20. Use POKE 36,T instead of TAB(T) (where T is the tab value) with either BASIC.

```
Print "first item";: POKE 36,45: Print "second item"
```

Output:

```
first item                second item
```

Tech Info Library Article Number:608