



Tech Info Library

Apple III Serial Port: Cable pinouts for Okidata 82A and 83A

Revised: 12/4/84
Security: Everyone

Apple III Serial Port: Cable pinouts for Okidata 82A and 83A

=====

Apple III Serial Port		Cable		Printer Connector
Frame Ground	(FG).....	1	<----->	1.....(FG)
Transmit Data	(Tx)	2	<----->	3.....(Rx)
Receive Data	(Rx)	3		
Request to send	(RTS)	4		
Clear To Send	(CTS)	5		
Data Set Ready	(DSR)	6	<----->	11
Signal Ground	(SG).....	7	<----->	7.....(SG)
Data Carrier Detect	(DCD)	8		
Secondary Clear To Send	(SCTS) ...	19		
Data Terminal Ready	(DTR)	20		

NOTE: Printer dip switches need to be set as shown:

FRONT	1 - OPEN	BACK	1 - CLOSED
	2 - OPEN		2 - CLOSED
	3 - OPEN		3 - OPEN
	4 - OPEN		4 - CLOSED
	5 - CLOSED		5 - OPEN
	6 - OPEN		6 - CLOSED
	7 - OPEN		
	8 - CLOSED		

NOTE: Jumper blocks should be in position A.

Apple Technical Communications

Tech Info Library Article Number:958