



Tech Info Library

Apple III: Printer Driver Data Configuration Block

Revised: 1/17/85
Security: Everyone

Apple III: Printer Driver Data Configuration Block

=====

NOTE: All values are in hexadecimal.

	0	1	2	3	4
Baud rate:					
110	03				
134.5	04				
300	06				
600	07				
1200	08				
1800	09				
2400	0A				
4800	0C				
9600	0E				

Data format:

7 data/odd parity	22
7 data/even parity	26
7 data/mark parity	2A
7 data/space parity	2E
8 data/no parity	00
6 data/odd parity	42
6 data/even parity	46
6 data/mark parity	4A
6 data/space parity	4E

Delay after CR:

			*		
--	--	--	---	--	--

Delay after LF:

			*		
--	--	--	---	--	--

Delay after FF:

				*	
	0	1	2	3	4

* In character times; may be any value from \$00 to \$FF.

Apple Technical Communications

Tech Info Library Article Number:1048