



# Tech Info Library

## Western DataCom WORLDCOM 200 modem: Using it with all Apples

Revised: 10/21/85  
Security: Everyone

Western DataCom WORLDCOM 200 modem: Using it with all Apples

=====

### Modem type:

AT&T 103/202/212A series; 1200 FDX, 1200 HDX, 0-300 bps.

### Instruction set used:

Fully HAYES compatible.

### Hardware configuration:

Three LED indicators on front panel give modem status. The modem is capable of dual speed operation, necessary for Europe and Australia phone systems. Built-in speaker is used to monitor operation and diagnostics.

### Software configuration:

Microprocessor controlled intelligent modem with auto-dial and auto-answer functions.

### Interface type:

RS-232 DB-25S (DCE) connector, full or half duplex operation.

### Modem interface packages, by computer:

#### Apple IIe (Super Serial card):

Access II or other terminal software; straight through DB-25 cable interface (serial card configured as DTE equipment) for hardware connection.

#### Apple IIc:

Access II or other terminal software; Apple IIc to Imagewriter cable with modem eliminator cable for hardware connection.

#### Apple III:

Access III or other terminal software; straight through DB-25 cable for hardware connection.

#### Macintosh:

MacTerm or other terminal software; Macintosh to Imagewriter cable with modem eliminator cable for hardware connection.

Macintosh XL:

MacTerm or other terminal software; straight through DB-25 cable for hardware connection.

Apple Technical Communications

Tech Info Library Article Number:1346