



Tech Info Library

Dot Matrix Printer Configuration Table (7/94)

Revised: 7/13/94
Security: Everyone

Dot Matrix Printer Configuration Table (7/94)

Article Created: 28 October 1985
Article Reviewed/Updated: 13 July 1994

TOPIC -----

This article details the Dot Matrix Printer configuration table.

DISCUSSION -----

System	SW-1	SW-2	CABLE REQUIRED
	12345678	12345678	Part Number
Apple III	11001010	00000110	590-0042B
Macintosh	N/A	N/A	N/A
Lisa/Macintosh XL	11001010	00000110	590-0042B
Apple IIc	N/A	N/A	N/A
Centronics Card	11001011	00000110	57-30360
2PIC	11001010	00000110	590-0042B

NOTE: 0 = OFF = OPEN
1 = ON = CLOSED

Apple III Driver Configuration

Driver	Data Configuration Block											
	0	_1_	_2_	_3_	_4_	_5_	_6_	_7_	_8_	_9_	_A_	_B_
PRINTER	60	40	00	00	64							

Parallel Interface Card (2PIC) Configuration

Switch Bank	_1_	_2_	_3_	_4_	_5_	_6_	_7_
SW1	Off	Off	Off	On	On	Off	Off

Article Change History:

13 Jul 1994 - Reviewed for technical accuracy, revised formatting.

Support Information Services

Copyright 1988-94 Apple Computer, Inc.

Tech Info Library Article Number:1428