



# Tech Info Library

## A/UX: How to Recover From a Corrupted Toolbox

Revised: 9/2/92  
Security: Everyone

A/UX: How to Recover From a Corrupted Toolbox

=====

Article Created: 31 May 1988  
Article Last Reviewed: 31 August 1992  
Article Last Updated : 31 August 1992

### TOPIC -----

What does the following error message indicate?  
/etc/toolboxdaemon: error opening user interface device: No such device

### DISCUSSION -----

The error message:  
  
/etc/toolboxdaemon: error opening user interface device: No such device

may mean that your toolbox user interface device may be corrupted or may have disappeared.

Check to see if the toolbox-specific device "/dev/uinter0" exists. The mode of toolbox-specific device should be:

```
crw-rw-rw-  1 root   sys      4,  0   May 3   16:30  /dev/uinter0
```

If this device file is corrupted or has disappeared, here is how to recover:

1. Bring the system to the single-user mode.
2. In single-user mode, type the command  
# /etc/newunix toolbox
3. Type the command  
# /etc/autoconfig -u -v -o /unix -S /etc/startup
4. Type the commands:

```
# sync  
# sync  
# sync
```

7. Reboot with the command  
# reboot

This should not happen in A/UX 2.0 and beyond.

Copyright 1988, 1992 Apple Computer, Inc.

Tech Info Library Article Number:2977