



# Tech Info Library

## AppleShare PC 1.1: Not Enough Memory For Installation

Revised: 5/24/89  
Security: Everyone

AppleShare PC 1.1: Not Enough Memory For Installation

=====  
This article last reviewed: 27 March 1989

Some users have had problems installing AppleShare PC 1.1. Here is a typical example:

The user has a Compaq 386/25 running DOS 3.3. The Compaq is configured with 640K base memory and 1280K extended memory and the following expansion boards: LocalTalk PC, Paradise EGA, Targa 16, and Compaq Multifunction controller board.

The user planned to have the Compaq and another PC share a LaserWriter IINT. After installing AppleShare PC, there is not enough memory to run applications. The memory problem is so severe that there was not enough memory to attach the LaserWriter through the DA.

In solving this type of problem, first consider how AppleShare PC uses memory. There is an AppleLink article titled "AppleShare PC Memory Use" in the Tech Info Library that describes the following:

The amount of memory used by AppleShare PC is:

- No resident DA or other options: 127,344 bytes
- DA resident with expanded memory option: 90,176 bytes
- DA resident (no graphics or memory options): 200,416 bytes
- DA resident and high-resolution graphics support: 215,776 bytes

DOS takes up approximately 40K. AppleShare PC with high-resolution graphics support for the EGA card and DOS will take up approximately 250K. This leaves 330K for applications. Major applications (word processors, spreadsheets, and so on) usually require 384K or 512K. No wonder the user runs out of memory.

In this kind of situation, do NOT install the DA into memory. Rather, activate the by running it as a program from DOS prior to executing the applications. The user can then make the connections to the printer before

executing applications.

The user does not have to execute the DA program each time the PC is turned on, if the ANET program is used and AppleShare PC is directed to connect to the LaserWriter or LaserWriters on startup. The ANET program is distributed with AppleShare PC.

Copyright 1989 Apple Computer, Inc.

Tech Info Library Article Number:3744