



# Tech Info Library

## Network Server: Status Panel Number Descriptions (5/96)

Revised: 5/21/96  
Security: Everyone

Network Server: Status Panel Number Descriptions (5/96)

=====  
Article Created: 21 May 1996

TOPIC -----

This article lists the more common values on the front status panel of the Network Server 500 and 700.

DISCUSSION -----

LCD System Action

- -----
- 510 The system has started the configuration manager.
  - 511 The configuration manager has completed.
  - 517 The system is attempting to mount the / (root) and /usr file systems.
  - 538 The configuration manager is passing control to a configuration method
  - 539 The configuration method has completed.
  - 551 The system is attempting to varyon the root volume group.
  - 553 The system has completed phase one of the boot process.
  - 591 The system is configuring the Logical Volume Manager (LVM).
  - 593 The system is configuring the low-function graphics terminal.
  - 594 The system is configuring the rendering context manager.
  - 704 The system is configuring a SCSI disk drive.
  - 723 The system is configuring a CD-ROM or other SCSI device.
  - 727 The system is configuring an asynchronous device.
  - 731 The system is configuring a pseudo TTY.
  - 811 The system is configuring the system planar (motherboard).
  - 812 The system is configuring the standard I/O adapter.
  - 814 The system is configuring the NVRAM.
  - 821 The system is configuring the standard keyboard adapter.
  - 823 The system is configuring the standard mouse adapter.
  - 826 The system is configuring on-serial port 1.
  - 828 The system is configuring the standard floppy disk adapter.
  - 831 The system is configuring serial port 2.
  - 868 The system is configuring the integrated SCSI adapter.
  - 874 The system is configuring the graphics subsystem adapter.
  - 921 The system is configuring a keyboard.

925 The system is configuring a mouse.

935 The system is configuring a 3.5-inch diskette drive.

9002 The system is configuring a SCSI-2 adapter.

Copyright 1996, Apple Computer, Inc.

Tech Info Library Article Number:19831