



# Tech Info Library

## ImageWriter II: Connecting to a VT320 Terminal

Revised: 5/26/88  
Security: Everyone

ImageWriter II: Connecting to a VT320 Terminal

=====  
This article last reviewed: 20 May 1988

Here's how to connect an ImageWriter II as a slave printer to a DEC VT320 terminal.

Acquire these parts:

DEC cable #BCE16E-xx (MMJ to MMJ) (xx = number of feet)

DEC adapter #H8751-F (MMJ to DB25 male)

Apple Cable M0333 (DIN-8 to DB25 female)

Set up the terminal-to-slave port as a printer port, and set the speed to 9600 baud. You can also select just the scrolling area as the print area, or the whole screen.

Remember to change DIP switch #3 on bank 2 to "off" on the ImageWriter. The printscreen key on the keyboard is the second from the left on the top row (it is usually labelled) and is functional.

Copyright 1988 Apple Computer, Inc.

Tech Info Library Article Number:2956