



# Tech Info Library

## ImageWriter II: Switch Settings for Use with a Apple IIe

Revised: 7/2/91  
Security: Everyone

ImageWriter II: Switch Settings for Use with a Apple IIe

=====  
This article last reviewed: 15 July 1990

TOPIC -----

What are the proper settings for using an Apple IIe with a Super Serial Card to an ImageWriter II?

DISCUSSION -----

The settings should be:

### Super Serial Card

SW1 1 off  
2 off  
3 off  
4 on  
5 off  
6 on  
7 on

SW2 1 on  
2 off  
3 off  
4 off  
5 on  
6 off  
7 off

Jumper block pointed toward terminal.

### ImageWriter II

SW1 1 off  
2 off  
3 off  
4 off

5 off  
6 on  
7 off  
8 off

SW2 1 on  
2 on  
3 off  
4 off

Cable: 590-0335 or 590-0556

Copyright 1991, Apple Computer, Inc.

Tech Info Library Article Number:7737