



# Tech Info Library

## LaserWriter Select 310: Pinouts (2/93)

Revised: 2/8/93  
Security: Everyone

LaserWriter Select 310: Pinouts (2/93)

=====  
Article Created: 9 February 1993

TOPIC -----

This article provides the pinouts for the LaserWriter Select 310's communications ports.

DISCUSSION -----

### Mini DIN-8 RS-232 Serial Communications Ports

Pin	Signal	Description
1	DTR	Data Terminal Ready (output)
2	DSR	Data Set Ready (input)
3	TxD-	Transmitted Data
4	SG	Signal Ground
5	RxD-	Received Data
6	SG	Single Ground
7	NC	No Connection
8	NC	No Connection
Shield	PG	Protective Ground

### Centronics Parallel Communications Port

Pin	Signal	Pin	Signal
1	Data Strobe	19	Ground
2	Data 0	20	Ground
3	Data 1	21	Ground
4	Data 2	22	Ground
5	Data 3	23	Ground
6	Data 4	24	Ground
7	Data 5	25	Ground

8	Data 6	26	Ground
9	Data 7	27	Ground
10	Acknowledge	28	Ground
11	Busy	29	Ground
12	Paper Out	30	Ground
13	(Select Printer)	31	No Connection
14	No Connection	32	(Printer error)
15	No Connection	33	No Connection
16	No Connection	34	No Connection
17	Signal Ground	35	No Connection
18	No Connection	36	No Connection

Copyright 1993, Apple Computer, Inc.

Tech Info Library Article Number:11520