



Tech Info Library

PowerBook: Using MacLink Plus With Only One Serial Port (3/95)

Revised: 3/31/95
Security: Everyone

PowerBook: Using MacLink Plus With Only One Serial Port (3/95)

=====
Article Created: 7 September 1994
Article Reviewed/Updated: 31 March 1995

TOPIC -----

This article provides instructions on using MacLink Plus by DataViz with a PowerBook that only has one serial port.

DISCUSSION -----

Powerbook 500 series with Internal Modem

Cable or modem connection through serial port

- Make AppleTalk inactive.
- In Powerbook Setup control panel, choose Normal (not Compatible).
- Set MacLinkPlus up for phone port.

Modem connection through internal modem

- In the Powerbook Setup control panel, choose Compatible (not Normal).
- In the PowerPort 500 control panel, turn the modem on.
- Set MacLinkPlus up for phone port.

Powerbook 500 series without Internal Modem

Cable or modem connection through serial port

- Make AppleTalk inactive.
- Select LaserWriter.
- Set MacLinkPlus up for Printer/Modem port.

Powerbook Duo with Express Modem, undocked

Cable or modem connection through serial port

- Make AppleTalk inactive.
- Select LaserWriter.
- Set MacLinkPlus to use the Printer/Modem port.

Do this by using one of the two methods below:

- In the Express Modem control panel, click on Status and change it to Settings, then choose External Modem (not Internal Modem).

Or

- If you cannot click on Status & change it to Settings, then open the Powerbook Setup control panel and choose Normal (not Compatible).

Modem connection through internal modem

-
- In the Express Modem control panel, choose Settings, then choose Internal Modem (not External Modem).
 - Set MacLinkPlus up for phone port.

Note: Docked, the Duo can be treated as any other Macintosh.

Powerbook Duo without Express Modem, undocked

Cable or modem connection through serial port

- Make AppleTalk inactive.
- In Powerbook Setup control panel, choose External Modem.

Note: This control panel may be called Portable, Powerbook, or Powerbook Setup.

- Set MacLinkPlus to use the phone port.

Modem connection through internal modem

-
- In Powerbook Setup control panel, choose Internal Modem.

Note: This control panel may be called Portable, Powerbook, or Powerbook Setup.

- Set MacLinkPlus to use the phone port.

Note: When docked, the Duo can be treated as any other Macintosh.

Article Change History:

31 Mar 1995 - Reviewed for technical accuracy.

Support Information Services

Copyright 1994-95, Apple Computer, Inc.

Tech Info Library Article Number:16226